



www.armadatech.com • (616) 803-1080

# Pro95i™ Advanced AC Leakage Clamp Multimeter



## Pro95i™ Features

- Measures AC Line Current in milliamps
- Measures AC or DC voltage, AC current, and resistance
- True RMS
- Alligator Clips Included
- Auto-Ranging Measurement
- Backlit Digital Screen
- Compact, Solid Design

## PRODUCT DESCRIPTION

The Pro95i™ Advanced AC Leakage Clamp Multimeter is perfect for 2-wire troubleshooting. The Pro95i makes it possible to diagnose cable and equipment faults in 2-wire systems without opening splices. The Pro95i measures AC line current with a resolution of 1 microampere simply by clamping over wires in a control cable. In addition, VAC, VDC, and ohms measurements are available. All utilize a built-in auto ranging function for easy use.

## PRODUCT FEATURES

- Contactless measurement of line currents down to 5 microamperes, a critical and necessary feature in diagnosing 2-wire faults
- True RMS measurement with automatic signal smoothing for improved accuracy
- Auto-off after 30 minutes idle
- Back-lit screen for dark areas

## SPECIFICATIONS

Current: Range from 5 microamperes to 60 amperes AC; Resolution to 1 microampere  
Voltage: VAC to 600V VDC to 600V  
Resistance: Automatically reads 0 to 600 Kohms, with selectable beep short circuit check  
Weight: Less than 1 lb. with packaging

## PACKAGE INCLUDES

- Pro95i™ Meter
- Carrying Case
- Test Probes with attachable alligator clips
- Instructions with a multilingual quick reference card
- Batteries

## ORDERING INFORMATION

CAT NO.	DESCRIPTION	QUANTITY
Pro95i™	Advanced AC Leakage Clamp Multimeter	1

Distributed by:



For more information contact:  
**Armada Technologies**  
8535 Byron Commerce Dr. SW  
Suite A  
Byron Center, MI 49315  
**Phone: (616) 803-1080**  
**Fax: (616) 803-1083**  
**[www.armadatech.com](http://www.armadatech.com)**